

UNITED STATES PATENT APPLICATION

FOR

METHOD FOR ASSIGNING CODES

IN UPLINK OF SYNCHRONOUS WIRELESS TELECOMMUNICATION SYSTEM

Inventor(s): **Duk-Kyung Kim**
Yoon-Seok Jung
Sang-Yun Lee
Jin-Young Kim

Prepared by:

BLAKELY, SOKOLOFF, TAYLOR & ZAFMAN
12400 Wilshire Boulevard, 7th Floor
Los Angeles, California 90025
(310) 207-3800

METHOD FOR ASSIGNING CODES
IN UPLINK OF SYNCHRONOUS WIRELESS TELECOMMUNICATION SYSTEM

Field of the Invention

[001] The present invention relates to a method for assigning codes in an uplink of a synchronous code division multiple access (CDMA) telecommunication system; and, more particularly, to a method for assigning codes in an uplink of a synchronous CDMA telecommunication system in which a signal to be transmitted is spread by an orthogonal code and then multiplied by a scrambling code based on a synchronization control message from a base station.

Description of the Prior Art

[002] A traffic channel between a base station and a mobile station in a conventional code division multiple access (CDMA) system includes a forward channel (downlink) and a reverse channel (uplink). At this time, multiple forward channels between the base station and multiple mobile stations located within coverage (cell) of one base station are synchronized with each other based on timing information. Therefore, when demodulating signals, interference between the channels can be considerably reduced by using orthogonal codes that are orthogonal from each other.

[003] However, in the reverse channel, since the timing information is not used, the reverse channels cannot be synchronized. As the number of the reverse channels is increased, the interference in the reverse channel is increased. Therefore, capacity of the reverse channel is limited.

0989954-070301

[004] To increase the capacity of the reverse channel, it is necessary for multiple reverse channels to be synchronized by using the same timing information. The reverse channels are synchronized, and then, the interference between the reverse channels can be minimized by identifying the channels based on the orthogonal codes each having orthogonality. This method is referred to as "an uplink synchronous transmission scheme (USTS)".

[005] One of core technologies necessary for the USTS is a code assignment, which has not been developed.

Summary of the Invention

[006] Therefore, it is an object of the present invention to provide a method for assigning codes so as to synchronize reverse channels in an uplink of a synchronous CDMA telecommunication system.

[007] In accordance with an aspect of the present invention, there is provided a method for assigning codes in a reverse channel of a synchronous wireless telecommunication system, comprising the steps of: a) at a mobile station, receiving time matching information of a scrambling code from a base station; b) at the mobile station, spreading data frame to be transmitted by an orthogonal code, thereby generating a spread data; and c) at the mobile station, multiplying the spread data by a scrambling code based on the time matching information of the scrambling code, thereby generating an encoded data.

[008] In accordance with another aspect of the present invention, there is provided a method for assigning a code in a reverse channel of a synchronous wireless telecommunication system, comprising the steps of: a) at

a base station, transmitting time matching information of a scrambling code to a mobile station; b) at a base station, receiving an encoded data which is scrambled based on the time matching information from the mobile station; and c) decoding the encoded data by despreading and descrambling the encoded data.

[009] In accordance with further another aspect of the present invention, there is provided a computer readable recording medium in a mobile station having a processor, which stores instructions for executing a method for assigning a code in a reverse channel of a synchronous wireless telecommunication system, the method comprising the steps of: a) at a mobile station, receiving time matching information of a scrambling code from a base station; b) at the mobile station, spreading data frame to be transmitted by an orthogonal code, thereby generating a spread data; and c) at the mobile station, multiplying the spread data by a scrambling code based on the time matching information of the scrambling code, thereby generating an encoded data.

[0010] In accordance with still further another aspect of the present invention, there is provided a computer readable recording medium in a base station having a processor, which stores instructions for executing a method for assigning a code in a reverse channel of a synchronous wireless telecommunication system, comprising the steps of: a) at a base station, transmitting time matching information of a scrambling code to a mobile station; b) at a base station, receiving an encoded data which is scrambled based on the time matching information from the mobile station; and c) decoding the encoded data by despreading and descrambling the encoded data.

[illegible]

[0012] Fig. 1 is a block diagram of an encoder applied to the present invention;

[0014] Fig. 3 is a flow chart of a code assigning method in an uplink of a synchronous wireless telecommunication system in accordance with the present invention.

[0015] Uplink synchronous transmission scheme (USTS) technology will be described in more detail.

4

station of the time offset from the reference time, such that each of the mobile stations can have the same reference time. The scrambling code which is multiplied to the multiple channels at the same time has the same number of chip.

[0029] When a first mobile station tries to set up a call, from front of the first frame to end of the last frame of a first channel of the first mobile station are multiplied by chips S_0 to S_{38390} of a scrambling code. When a second mobile station tries to set up a call during communication between the first mobile station and the base station, from front of the first frame to end of the last frame of a second channel are multiplied by chips S_{5120} to S_{38390} and S_0 to S_{5119} of the scrambling code.

[0030] The second channel is delayed from the first channel by the time offset $_ (256 \times n \text{ chip})$, however, the scrambling code multiplied by the data frame in the second channel at time A is S_{5120} which is the same as the first channel. At time B, one frame of the first channel is end and the frame of the second channel is not end, however, the scrambling code of the second channel is newly started as the same as that of the first channel.

[0031] Therefore, the data frame in the channel for each of the mobile stations is multiplied by the same scrambling code at the same time. The decoder of the base station can entirely obtain the data from the mobile stations by descrambling the received signals which are synchronized and can reduce interference between the channels by despread the descrambled signals.

[0032] Here, the scrambling code and the frame has the same length, 38400 chips, and the scrambling code is

multiplied by one frame. A slot has a length of 2560 chips, the orthogonal code is repeatedly multiplied by 256-chip (1/10 slot) of the data frame.

[0033] Fig. 3 is a flow chart of a code assigning method in an uplink of a synchronous wireless telecommunication system in accordance with the present invention.

[0034] A mobile station receives a synchronization control message from a base station at step S31. The synchronization control message includes time matching information that m -th slot of the spread data should be multiplied by n -th chip of the scrambling code. Here, m and n are integer numbers larger than 0.

[0035] Data frames to be transmitted are inputted to an encoder bit by bit at step S33.

[0036] In the mobile station, one data frame, 150 bits, is divided into 15 slots, and one slot is multiplied by a 256-chip orthogonal code, thereby spreading a bit into 256 chips at step S35. One frame is spread into 38400 chips.

[0037] The spread data is multiplied by the scrambling code based on the time matching information of the synchronization control message, thereby generating an encoded data at step S37. In other words, the spread data is multiplied by the scrambling code corresponding to the start slot of the frame based on the synchronization control message. By multiplying the same scrambling code to the channels of all mobile stations in the same cell at the same time, the decoder of the base station can perform accurate descrambling of the received signals from the mobile stations.

[0038] The encoded data is transmitted to the base station at step S39.

[0039] Using the code assigning method according to the

present invention, the uplink synchronous transmission scheme is implemented, and the interference between the reverse channels can be minimized, to thereby increase capacity of the base station. By synchronizing the channels, orthogonality between the channels can be effectively used, thereby increasing quality of the communication.

[0040] Although the preferred embodiments of the invention have been disclosed for illustrative purposes, those skilled in the art will appreciate that various modifications, additions and substitutions are possible, without departing from the scope and spirit of the invention as disclosed in the accompanying claims.